



No Limits on Performance!



www.microtouchinc.com



Red Wire --

12 volt (Red) on Battery

Black Wire --

Ground (Black) on Battery


Yellow Wire --

Plug Wire Pick-up



Wrap 3 - 4 times around each plug wire!

Gray / Black- Red --



To Solenoid (Polarity does NOT matter)





On @ 2,000 RPM
 Buzz 1 5/8 6,750 RPM
 Buzz 2 4/8 6,900 RPM
 Buzz 3 3/8 7,050 RPM
 Buzz 4 2/8 7,200 RPM
 Off @ 7,350 RPM


On @ 2,000 RPM
 Buzz 1 5/8 6,400 RPM
 Buzz 2 4/8 6,500 RPM
 Buzz 3 3/8 6,600 RPM
 Buzz 4 2/8 6,700 RPM
 Off @ 6,800 RPM

On @ 2,000 RPM
 Buzz 1 5/8 6,950 RPM
 Buzz 2 4/8 7,050 RPM
 Buzz 3 3/8 7,150 RPM
 Buzz 4 2/8 7,250 RPM
 Off @ 7,350 RPM

On @ 2,000 RPM
 Buzz 1 5/8 6,200 RPM
 Buzz 2 4/8 6,300 RPM
 Buzz 3 3/8 6,400 RPM
 Buzz 4 2/8 6,500 RPM
 Off @ 6,600 RPM



| Legend | |
|---|--------------|
|  | = Jumper ON |
|  | = Jumper OFF |

NOTE:

Keep controller mounted a few inches away from ignition coils or plug wires.
Also keep grease on the fuse and the adjusting jumpers at all times to eliminate corrosion!