

Data Sheet for Micro Touch Rev-Limiter
Sea•Doo® 89 - 91 Models



RPM Settings	Jumpers			
	1	2	3	4
6,500	■	■	■	■
6,750	■	■	■	●●
7,000	■	■	●●	■
7,250	■	●●	■	■
7,500	●●	■	■	■
7,750	■	●●	●●	■
8,000	●●	■	●●	■
8,100	■	●●	■	●●
8,200	●●	●●	■	■
8,300	●●	■	■	●●
8,400	■	■	●●	●●
8,500	●●	●●	●●	■
8,600	●●	●●	■	●●
8,700	●●	■	●●	●●
8,800	■	●●	●●	●●
8,900	●●	●●	●●	●●



Fits ALL 89-91 Sea•Doo
Watercraft Sp's and GT's

Legend

■ = Jumper - ON
●● = Jumper - OFF

MT-REV-SD 89-91

Jumpers
1 - 4

Wires

NOTE:
This Setting above is
7,250 RPM's Limit

Note: Use Dielectric grease on all connections and jumpers. Also make sure that all connections are tight fitting. The connectors will spread apart over time and can be crimped with pliers. If this does not work replace the connector.